KENWOOD



TK-2000/3000

Compact VHF/UHF FM Portable Radios





The Thin Edge

Slim, thin and light – Kenwood's TK-2000/3000 is supremely easy to handle and to operate. Yet this handy compact radio is extremely reliable, meeting the famously tough MIL-STD 810 C/D/E/F and G specifications. With its well-balanced performance, it makes perfect business sense – especially for inventory control and service industry operations.

Thin & Lightweight

Thinner and lighter – the TK-2000/3000 is ideal for hooking on a belt or even slipping into a coat pocket. The slim design fits neatly in your hand and it weighs only 203g with the KNB-63L battery.



16 Channels with Scan Function

This compact, user-friendly portable offers a total of 16 channels, and each can be assigned a QT and DQT tone key to eliminate unwanted signals. You can also assign the 16th channel, if free, to the scan function. This added convenience means that the PF key is freed up for some other function.

Programmable Function Key with Hold

The side PF key can be programmed for enhanced operating ease, while the adjustable Hold feature doubles the number of functions at your fingertips.

All-in-one Package

The TK-2000/3000 is ready for use immediately after purchase. It comes with all necessary accessories, including a charger, battery pack and antenna. A handy belt clip is also provided. There is no need to buy extra accessories for normal operation.

Supplied Accessories • Charger • Charger • Charger • Battery • Belt Clip

Robust & Reliable

The TK-2000/3000 is built to survive hard knocks, drops and all-weather environments. It meets or exceeds the stringent IP54 dust and water intrusion standards as well as the MIL-STD 810 C, D, E, F & G environmental standards.

OTHER FEATURES

- Output Power 5W (VHF) / 4W (UHF) QT / DQT
- DTMF Enc. (PTT ID, Autodial) Priority Scan
- Windows® Programming and Tuning
- Wide/Narrow Channel Bandwidth
- VOX Ready
 Battery-Saver
- Busy Channel Lockout Time-Out-Timer
- Low-Battery Alert
 Tri-Colour LED
 Wired Clone



Options



All accessories and options may not be available in all markets. Contact our authorized dealer for details and complete list of all accessories and options.

Specifications

	TK-2000	TK-3000		TK-2000	TK-3000	
SENERAL			RECEIVER			
requency Range	144 - 174 MHz	440 - 470 MHz	Sensitivity (Wide / Wide 4K / N	larrow)		
lumber of Channels	16 channels		EIA 12dB SINAD	0.28 μV / 0.28 μV / 0.35 μV		
hannel Spacing			EN 20dB SINAD	-3 dB μV (0.35 μV) / -3 dB μV	-3 dB μ V (0.35 μ V) / -3 dB μ V (0.35 μ V) / -1 dB μ V (0.45 μ V	
Wide / Wide 4K / Narrow			Adjacent Channel Selectivity			
perating Voltage 7.5 V DC ± 20 %		Wide / Wide 4K / Narrow	70 dB / 70 dB / 60 dB			
Battery Life (5-5-90 duty cycle)			Intermodulation Distortion	65	65 dB	
with KNB-63L	L Approx. 9 hours		Spurious Response Rejection	70	70 dB	
with KNB-65L	Approx. 12 hours		Audio Distortion	Less th	Less than 5 %	
Operating Temperature Range -20°C ~ +60°C		Audio Output	500 m	500 mW / 8 Ω		
requency Stability	5 ppm	2.5 ppm	TRANSMITTER			
ntenna Impedance	50		RF Power Output (High / Low)	5 W / 1 W	4 W / 1 W	
Channel Frequency Spread 30 MHz		Modulation Limiting	±5.0 kHz at 25 kHz			
Dimensions (W x H x D), Projections not Included				±4.0 kHz at 20 kHz		
Radio only	54 x 113 x 14 mm			±2.5 kHz at 12.5 kHz		
with KNB-63L	54 x 113 x 24.9 mm		Spurious Emission	-36 dBm ≤ 1GHz	-36 dBm ≤ 1GHz, -30 dBm > 1GHz	
with KNB-65L	54 x 113 x 26.9 mm		Modulation		***************************************	
/eight (net)			Wide / Wide 4K / Narrow	16K0F3E / 14K	OF3E / 11K0F3E	
Radio only Approx. 130 g		FM Noise (EIA)				
with KNB-63L	Approx. 203 g Approx. 222 g		Wide / Wide 4K / Narrow	45 dB / 43	3 dB / 40 dB	
with KNB-65L			Modulation Distortion	Less th	Less than 5 %	
pplicable Standards			Microphone Impedance	1.8	1.8 kΩ	
ETSI R&TTE		300 219, EN 301 489	3000011000011000011100011100011100011100011			
ETSI Safety	EN 60065, EN 60950-1, EN 60215		Analogue measurements made per EN Standards and specifications shown are typical.			
			Specifications are subject to chang Windows® is a registered tradema			

Applicable MIL-STD & IP

MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
500.1/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II	500.5/Procedure I, II
501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II	502.5/Procedure I, II
503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II	503.5/Procedure I
505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I	505.5/Procedure I
506.1/Procedure II	506.2/Procedure II	506.3/Procedure II	506.4/Procedure III	506.5/Procedure III
507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4	507.5/Procedure II
509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4	509.5
510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III	510.5/Procedure I
514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I	514.6/Procedure I
516.2/Procedure I, II, V	516.3/Procedure I, IV	516.4/Procedure I, IV	516.5/Procedure I, IV	516.6/Procedure I, IV
	Methods/Procedures 500.1/Procedure 501.1/Procedure 501.1/Procedure 502.1/Procedure 503.1/Procedure 505.1/Procedure 506.1/Procedure 507.1/Procedure 509.1/Procedure 510.1/Procedure 510.1/Procedure 510.1/Procedure	Methods/Procedures	Methods/Procedures Methods/Procedures	Methods/Procedures Methods/Procedures Methods/Procedures

To meet MIL810 and IP54, the 2-pin connector cover has to be connected.

Kenwood Electronics U.K. Ltd.

Kenwood House, Dwight Road, Watford, Herts, WD18 9EB, United Kingdom www.kenwood-electronics.co.uk

